Accessories :

Features :

- Tool-free, left-mounted on the MCBs.
- Maximum of 3 accessories can be installed on to a single circuit breaker at once.
- Maximum of 2 auxiliary switch (AX) can be installed on to a single circuit breaker at once.

Type designation :

BHK

•Accessories

BHK	–	B10
↓		↓

Type	Accessory Code				
	B10	B20	B30	B40	B50
BHK	AL	AX	SHT	UVT	OVT

Note: 1. AL/AX can only be installed on the left side of SHT/UVT

Type	Auxiliary Contact AC/12	Width (mm)	Product Code
AL Alarm Switch	AC415V 3A AC240V 6A DC130V 1A DC48V 2A DC24V 6A	9	BHK-B10
AX Auxiliary Contact	AC415V 3A AC240V 6A DC130V 1A DC48V 2A DC24V 6A	9	BHK-B20

Type	Control Voltage		Control Voltage	Width	Product Code
	V AC	V DC	AC/12	(mm)	
SHT Shunt Trip	24~48 110~415	24~48 110~415	AC 24~48V DC 24~48V AC/DC 110~415V	18	BHK-B30
UVT Under Voltage Trip	230	48	<170V±5%	18	BHK-B40

Type	Rated Voltage	Current	Over voltage Range	Trip time	Width (mm)	Product Code
OVT Over Voltage Trip	230V	10mA	275V±5%	< 0.1S	18	BHK-B50